



INITIAL FINDINGS




Electronic
Parts
Engineering

- 72 Hour Vacuum Bake Followed By Sealing RGA Holes
(Electrical Performance Normal for all Channels)
- 160 Hour Burn-in @ +85C, DC Bias (1 of 7 channels
drifted slightly)
- 96 Hour Bake @ +93C (all channels drifted)
- RGA Testing
 - ◆ Met Internal Water Vapor Content Requirement:
1.7%
 - ◆ Hydrogen: 1776ppm

*tantalum nitride
hybrid
microelectronics
palladium*



IDENTIFICATION OF PROBLEM



- Empirical Circuit Analysis Identified two 35k ohm Tantalum Nitride Resistors that set the bias voltage for each side of a LM194 or a MAT02 matched dual NPN transistor to be very sensitive.
- Computer circuit simulation confirmed this finding. A 20 ohm differential shift in the set resistance values between the 2 chips would result in the observed frequency output drifts.
- EDAX Analysis of the 35k ohm thin film Tantalum Nitride chip resistors identified Palladium in the film.
- A catalytic reaction of Palladium and Hydrogen produces mono atomic hydrogen.
- Filled the filter module cavities with a 4% Hydrogen, 96% Nitrogen gas mixture @ 25°C and monitored the electrical performance for 24 hours. Some channels drifted in a similar pattern witnessed earlier.
- An internal visual and EDAX analysis was performed at the conclusion of this testing. Confirmed Palladium on chip resistors.



X-RAY EDS OF TANTALUM NITRIDE RESISTOR



Electronic
Parts
Engineering

9-Feb-1999 11:34:40

ELEMENT


Vert =

1000 counts Disp = 1

10KV


Preset =
Elapsed =

100 secs
100 secs





HYPOTHESIS



- When burn-in was performed on hermetically sealed filters at +125°C, hydrogen was desorbed out of the Kovar carriers, epoxy and plated parts and into the air inside each hybrid MIC module.
- A catalytic reaction between the hydrogen and the palladium in the 35k ohm Tantalum Nitride resistors subsequently resulted in slight shifts in their resistance values.
- Due to the design of the analog section, these slight shifts resulted in very large changes in the static output frequency of the filter module channels.



SUPPORTING DATA



Electronic
Parts
Engineering

- Final RGA test: 1776ppm Hydrogen, 97.8% Nitrogen, 1.57% Moisture
- Electron Dispersion X-Ray Detector (EDAX) identified Palladium in Tantalum Nitride resistor films.



POST 96 HOUR BAKE RGA DATA



Electronic
Parts
Engineering

Hydrogen	0.1775% (1776 PPM)
Nitrogen	97.8073%
Moisture	1.5681% (pass, <5%)
Oxygen	0.2258% (2258 PPM)
Carbon Dioxide	0.1397% (1397 PPM)
Argon	0.0218% (218 PPM)
MEK	0.0540% (540 PPM)
Hydrocarbon	0.0057% (57 PPM)



DRY AIR



Electronic
Parts
Engineering

Nitrogen (N2)	78.09%
Oxygen (O2)	20.95%
Argon	0.93%
CO2	0.03%
Neon	0.0018%
Helium	0.00052%
Methane (CH4)	0.00011%
Krypton	0.0001%
Hydrogen (H2)	0.00005% (0.5 PPM)
Ozone (O3)	≤0.00005%
Xenon	0.0000087%
CO	≤0.00005%
N2O	0.0000003%
SO2	≥0.0000007%

Nitric Oxide, Nitrogen Dioxide, Formaldehyde, Ammonia (NH3)

Effects of Hydrogen, SoCal'99



INITIAL RGA TEST DATA



Electronic
Parts
Engineering


<u>GAS DETECTED</u>	<u>MODULE 1</u>	<u>MODULE 2</u>
Hydrogen	0.4036% (4036ppm)	0.1930% (1930ppm)
Nitrogen	65.7737%	77.6249%
Helium	23.6097%	7.7489%
Moisture	7.9643%	6.7730%
CO2	1.8147%	1.4550%
Oxygen	2747ppm	5.7011%
MEK	886ppm	779ppm
Argon	248ppm	3933ppm
Other:	Hydrocarbon, Krypton, THF (all <156ppm)	



X-RAY EDS OF RESISTOR CHIP IN HYBRID



Electronic
Parts
Engineering





SOURCES OF HYDROGEN



Electronic
Parts
Engineering

- Ferrous Metal Package Materials, trapped in metal at structural imperfections, grain boundaries, precipitate interfaces, dislocation cores. (Cold Rolled Steel, Kovar, Invar)
- Gold and Nickel Plating Process.
- Microwave Absorbers (powdered iron filings suspended in a carrier such as silicone rubber)
- Epoxy is suspected as a source.
- Capacitors, Circulators, Isolators, Ferrite Pucks, Circuit Substrates, Resistors and Metal Films may be sources.



SIGNIFICANT INFORMATION



Electronic
Parts
Engineering

- Research theory assumes a catalytic reaction with Palladium and molecular Hydrogen forming mono atomic hydrogen. In GaAs Semiconductors this results in compensation of donors in the channel or a shift in barrier height.
- A 10 to 20 ohm delta shift in resistance value between the two 35k ohm tantalum nitride resistors will result in the observed output drift.
- Modifications as a result of this study, using a center tapped dual tantalum nitride resistor, replacement of Kovar carrier with molybdenum, improved electrical grounding, proper 24 hour pre-seal vacuum bake and the addition of a hydrogen getter.
- Static output frequency has stabilized by a factor >100 times and there is no longer any frequency drift during burn-in testing of the hermetic cavity.



CORRECTIVE ACTION




Electronic
Parts
Engineering

- Change Kovar carriers to Copper-Molybdenum.
- Add Hydrogen Getter from Allied Signal Aerospace (HMC Getter) which can maintain hydrogen levels to <1 PPM and the dew point <-100°C
- Open package thermal treatment bake-out at 100 to 110°C.
- Perform 24 hour Vacuum Bake at +85°C prior to welding cover over module in a dry Nitrogen/Helium gas environment.
- Lower Burn-In temperature to +85°C.
- Replace the two 35k ohm single chip Tantalum Nitride resistors with a dual center tap resistor.
- Locate resistors from a supplier that does not use Palladium in their process.
- Maintain hybrid module temperature below +85°C during all post seal process and screening tests.



SUMMARY



- Isolated Failure Mechanism
- Developed a Hypothesis
- Supported Hypothesis
- Modified Hybrid Design in Accordance With Hypothesis and Other Problems With Circuit.
- Demonstrated new circuit design was now stable.
- Identified new concern with tantalum nitride chip resistors for hydrogen desorbed inside a hermetic microelectronic hybrid device.